

Evax Systems Cabinets

Evax Systems offers a number of different cabinets available for the mounting of voice evacuation component parts.

Each of the cabinets is available painted Charcoal Gray or Red, and includes a hinged locked door with a dead front cover, and provides means for mounting system components, including the transformer, the EVAX 25 - 50 - 100 Master Panel, EVX-25 - 50 - 100E Expander Modules, EVX Series Zone Splitters and standby batteries.

All cabinets can be installed as either surface mount or semi flush mount cabinets. Two "keyholes" are provided at the top of each box, and two through holes are provided at the bottom of each box for fastening.

Knockouts are provided on the sides of the box, and on the back of the box for the connection of conduit for field wires.

Space is provided in the back box for 2 standby batteries (4 in the EVX-CAB-2) up to 12 AH in size.

Cabinet Type	Back Box Rough-In Dimensions	Door Finished Dimensions
EVX-CAB-1(R)	14 ½" x 18" x 4"	16 ¼" x 19 ½"
EVX-CAB-2(R)	14 ½" x 27" x 4"	16 ¼" x 28 ½"
EVX-CAB-RM	8" x 10" x 2 ¾"	9 ½" x 11 ¼"

Battery Space in cabinets: $w \cdot h \cdot d$

EVX-CAB-1 w/Dead Front	14 ½" x 5 ½" x 3¾"
EVX-CAB-1 w/o Dead Front	14 ½" x 5 ½" x 4½"
EVX-CAB-2 w/Dead Front	14 ½" x 5" x 3¾"
EVX-CAB-2 w/o Dead Front	14 ½" x 5" x 4½"
MX-M-CAB	14 ½" x 4" x 2½"